

# A60 60W Incandescent Equivalent



**Feature:**

- Economic light sources for most luminaires such as pendant light, ceiling light, down light, etc.

**Product Number:**

BLP1927P25-TWW1207H2  
 BLP1927P25-TNW1207H2  
 BLP1927P25-T65W1207H2

\*Contact our sales for more details

**Certification:**



**Electrical Specification**

| Input Voltage | Power | Frequency | Power Factor | Dimming | Energy Efficiency Class |
|---------------|-------|-----------|--------------|---------|-------------------------|
| 220-240V      | 9     | 60 Hz     | >0.5         | NO      | F                       |

**Optical Specification**

| Total Flux        | Rated Flux | STD CCT    | STD CRI | Beam Angle | CBCP |
|-------------------|------------|------------|---------|------------|------|
| 510 lm            | 510 lm     | 3000K      | 80      | 220°       |      |
| CCT Option        |            | CRI Option |         |            |      |
| 3000K/4000K/6500K |            | 90         |         |            |      |

**Dimension & Packing Information**

|                |                   |                 |       |
|----------------|-------------------|-----------------|-------|
| Size           | Ø60*108 mm        | Unit Net Weight | 50g   |
| Packing Method | 50 PCS per Carton |                 |       |
| Packing Size   | 365*365*275 mm    | Gross Weight    | 3.5KG |

**Other Information**

| Lamp Base | Operation Temperature | Storage Temperature |
|-----------|-----------------------|---------------------|
| E27       | -20-40°C              | -20-70°C            |

## Safety Instructions:

- The products should be used with the specified wattage from appropriate equipment to prevent breakage or overheating.
- Operate the products in the appropriate position to prevent damage or overheating.
- Turn off the electrical power while installing, removing, or cleaning the products.
- Keep the products out of reach to the children.
- Avoid to use in high humidity locations unless necessary ingress protection is marked.
- Avoid to use where high volume of flammable substance such as gasoline or dust in the air.
- Avoid to use adjacent to flammable substances such as gasoline, paints, lacquer, and oil etc.
- Avoid to use in acid environment.
- Avoid to use where impact or vibration is likely to occur.
- Do not use bare hand or stained gloves to install, remove, or clean the products.
- Do not cover the products with paper, fabric, or any flammable substance.
- Do not insert metal objects into the gaps of the products.
- Do not disassemble or reconstruct the products.
- Do not stare directly the products while they are turned on.
- Do not wash the products by water or any detergent.
- Do not install the products in the sealed fixture unless specified in datasheet.
- Do not install the products on damaged sockets.
- Do not paint, dye, or put colors on the products.

## Transformer selection guide for low voltage lamp:

There are 3 different types of transformer are used for 12V products

- Electronic AC Transformer
- Magnetic AC Transformer
- DC Transformer

The Electronic Ac transformer is mainly used for traditional halogen lamp. LED based product may have flicker or being off while connecting the Electronic AC Transformer.

## Dimmer selection guide for low voltage lamp :

Traditional Triac dimmer only works for AC transformer. Therefore, the dimming effect depends heavily on the combination of dimmer and transformer. Please contact us for more information.

## Dimming guide for dimmable lamp:

Our dimmable products can work with most of the leading edge and trailing edge dimmers but we cannot guarantee problems such as flicker or noise will not happen in all dimmers in the market.

Most dimmers can be loaded with LED light source up to 20% of its typical power.

When dimmer is off, the LED light source may still emit a tiny and visible light.

Mixed load may cause unexpected dimming behavior or even defects, which is not belong to the quality guarantee.

Minor noise or flickers may occur while tuning dimmers. Please adjust the dimmer until the light tuned to a steady level